



FOSSiBOT F2400 Portable Power Station User Manual

[Home](#) » [FOSSiBOT](#) » FOSSiBOT F2400 Portable Power Station User Manual 

Contents

- 1 FOSSiBOT F2400 Portable Power Station
- 2 Product Information
- 3 Precautions for Use
- 4 Product Usage Instructions
- 5 Charging
- 6 UPS Mode
- 7 Solar Panel Connection
- 8 Car Charging
- 9 Fan Cover
- 10 Troubleshooting
- 11 Warranty
- 12 PRECAUTIONS FOR USE
- 13 Product Introduction
- 14 Button Function Introduction
- 15 Introduction of Display Interface
- 16 The Screen Displays Precautions
- 17 UPS Mode
- 18 Connection of Solar Panels
- 19 Car Charging
- 20 Use of Fan Covers
- 21 Product Specifications
- 22 Troubleshooting
- 23 Warranty
- 24 Documents / Resources
- 25 Related Posts





Product Information

The Fossibot F2400 portable power station is a 2048Wh large-capacity 2400W high-power portable power station that comes with a lithium iron phosphate battery that provides extremely high safety performance. It can be used as a backup power supply in the event of a sudden power failure or a disaster, or used for camping and living power in a camper. It can also provide power for various power tools regardless of the occasion. The product comes with a car charging cable and AC cable and can be charged directly from the wall socket.

Precautions for Use

- Avoid long-term storage and use of this product in environments with high temperature and humidity or direct sunlight to avoid shortened battery life and other failures.
- This product must not be disassembled or modified.
- Be careful not to drop or drop the product from a high place, so as not to damage the product.
- Please store or use this product out of the reach of children.
- Please use our original accessories, and Fossibot will not guarantee the defective products caused by the use of non-original accessories.
- Please directly plug in the wall socket to charge the product, do not use extension cords or cable taps.
- When the product is not in use or idle, please turn it off and unplug the power cable.
- If the product reaches scrap conditions, please discard or recycle the product in accordance with local laws.

Product Usage Instructions

Before using the Fossibot F2400 portable power station, please read the user manual carefully. The user manual

is required for product warranty. Keep the user manual together with the purchase certificate such as the invoice.

Charging

The Fossibot F2400 portable power station can be charged directly from the wall socket. Do not use extension cords or cable taps when charging the product. When using two or more sockets to charge, do not use devices other than this product on the same socket. To fully charge the product, please plug it into the wall socket and wait for it to charge for 2 hours.

UPS Mode

The Fossibot F2400 portable power station has a UPS mode that allows it to switch to battery power when the input power fails. To use this mode, plug the power cable of the device you want to protect into the AC output of the portable power station, then press and hold the power button for 3 seconds to switch to UPS mode.

Solar Panel Connection

You can connect a solar panel to the Fossibot F2400 portable power station to charge it. The solar panel must have a rated output voltage of 18V-24V and a maximum output current of 10A. To connect the solar panel, plug the MC4 connector of the solar panel into the Anderson input port of the portable power station.

Car Charging

The Fossibot F2400 portable power station can also be charged using a car charging cable. To charge it, plug one end of the car charging cable into the car cigarette lighter and the other end into the DC input port of the portable power station.

Fan Cover

The Fossibot F2400 portable power station comes with a fan cover that can be used to protect the fan from damage during transportation. To use the fan cover, place it over the fan and fasten it with the straps.

Troubleshooting

If you encounter any problems with the Fossibot F2400 portable power station, please refer to the troubleshooting table in the user manual.

Warranty

The Fossibot F2400 portable power station comes with a warranty. Please refer to the user manual for details on the warranty and how to make a claim.


PRECAUTIONS FOR USE

1. Please avoid long-term storage and use of this product in environments with high temperatures and humidity or direct sunlight to avoid shortened battery life and other failures. The product should not be close to the fire source, otherwise, it may cause a major fire or accident.
2. This product must not be disassembled or modified. Improper operation may cause product malfunction or even fire.
3. Be careful not to drop or drop the product from a high place, so as not to damage the product.


4. Please store or use this product out of the reach of children, otherwise, the product may be dropped or collided and may cause bodily injury to children.
5. Please use our original accessories, and Fossibot will not guarantee the defective products caused by the use of non-original accessories.
6. Please directly plug in the wall socket to charge the product, do not use extension cords or cable taps, otherwise, there is a risk of damage to the extension cords and cable taps or even a fire; If the extension socket is plugged in to charge this product, please do not connect other electrical appliances to this socket, otherwise, the household energy meter may trip.
7. When the product is not in use or idle, please turn it off and unplug the power cable. If it needs to be idle for a long time, please consume the product from a fully charged state to an uncharged state, then recharge it to about 50% of the battery level and store it. In order to prolong the life of the product, please take three months as a cycle, operate and keep it in this way.
8. If the product reaches scrap conditions, please discard or recycle the product in accordance with local laws.

Thank you for purchasing Fossibot F2400 portable power station. Please carefully read the user manual before operating the product. This user manual is required for product warranty. Please keep this user manual together with the purchase certificate such as the invoice. Due to the transportation requirements of international customs for battery products, F2400 is charged to about 30% before delivery. Please fully charge the product after unpacking for use. This product should be charged directly from the wall socket. Do not use extension cords and cable taps. When using two or more sockets to charge, do not use devices other than this product on the same socket.

OUTLET TYPE: AC OUTPUT



Packing list




Portable
Power Station



Car Charging
Cable



AC Cable



Anderson to MC4




User Manual

Product Introduction


This product is a 2048Wh large-capacity 2400W high-power portable power station supplied with 2-hour high-speed charging, using a lithium iron phosphate battery with extremely high safety performance. It can be used as

a backup power supply in the event of a sudden power failure or a disaster, or used for camping and living power in a camper, and can also provide power for various power tools regardless of the occasion. 2400W high power, sine wave AC output, can be used for high-power household appliances such as dryers, microwave ovens, refrigerators, induction cookers and electric ovens; it can also be used for other electronic devices such as personal computers. 0-100% charging can be completed within 2 hours through the 1100W ultra-fast charging of the household power socket, and the input voltage frequency can be auto-switched to 50Hz/60Hz, or the input voltage frequency can be manually switched to 50Hz/60Hz. In addition, this product also supports solar panel charging, and the maximum input power cannot exceed 500w, allowing you to charge outdoors or at home when there is a power outage.




Button Function Introduction

1. 1 Power ON/OFF Button
2. LED Light Button (Switch to different mode)
3. USB ON/OFF Button
4. DC ON/OFF Button
5. LCD Screen
6. Input Power Knob



7. Cooling Air Duct
8. AC Switch (Manually Switch to 50/60Hz)
9. Anderson Input Port (For Solar Panel)
10. AC input
11. Overload Protection Button



Power ON/OFF Button

- Instructions: Press and hold the power button for 3s to wake up the system, turn on the LCD display, and press and hold again for 3s to turn off.

Light Button

- Instructions: Short press the Light button, the LED light is on; short press again, the LED light enters the SOS mode, short press in turn, enter the strobe mode, and finally the LED light turns off (LED in any mode, long press the LIGHT button for ≥ 1 second, directly turn off the LED light).

USB ON/OFF Button

- Instructions: Short press the USB button to turn on the USB output port, and short press it again to turn it off.

		
USB-A	TYPE-C X 3	TYPE-C X 1
<hr/>		
QC 3.0	PD-20W	PD-100W

DC ON/OFF Button

- Instructions: Short press the DC button to turn on the DC output port, and short press it again to turn it off.

		
DC output × 2	Cigarette port × 1	XT60 × 1
12V/3A	12V/10A	12V/25A

LCD Screen

- Display the product's battery level and usage status tips.

Input Power Knob

- When the product is connected to the AC mains for charging, the power can be adjusted according to the actual input voltage. The clockwise rotation increases the input power, and the counterclockwise rotation decreases the input power. It is worth noting that charging this product at low power is beneficial for extending battery life.

Cooling Suction/Exhaust Port

When the product reaches the temperature threshold set by the system, the cooling fan will automatically run, accompanied by a certain fan noise (fan noise below 60dB is normal). Do not block the cooling suction/exhaust port during use of this product, and do not place any object within the range of 30CM.

AC Switch (AC output port, the sum of electrical load power should be <2400W)

Tap the AC button to enable the AC output function.

Notices

1. Since there may be differences in the AC output frequency in different regions, please check the AC voltage and frequency of the device before use.
2. Press and hold the AC button for 2 seconds to enter the frequency switching mode, the 50Hz or 60Hz icon will flash on the display. Short press the AC button again to select 50Hz or 60Hz; when the icon stops flashing and displays 50Hz or 60Hz, it indicates the switch is successful.
3. Short press the AC button 10 times in quick succession in the United States and Japan to switch the AC output voltage to 100V or 110V.
4. Short press the AC button 10 times in quick succession in China, United Kingdom, Europe and Korea regulations to switch the AC output voltage to 220V or 230V.

Anderson Port

Connect the solar panel using the Anderson to MC4 cable.

1. The input of the solar panel can be up to 500W and the maximum voltage is 50V.
2. If the equipment is damaged by exceeding the maximum voltage, it is outside the scope of warranty.

AC Input

- 1100W fast charging with a household socket can perform a 100% charge within 2 hours.
- The charging of this product can directly use the socket on the wall, etc. Please do not use extension cords and cable taps to connect several devices at the same time.
- Using a cable tap to charge several devices at the same time will cause a large current to flow, causing cable breakage and fire risk.
- Do not use the same socket to connect other devices while charging this product. In general, when the same wiring in the family exceeds 1500W, the safety circuit breaker will start.


Overload Protection Button

When the power supply voltage is unstable due to lightning or other reasons, and there is a large voltage input at the AC Input, in order to protect the product, the overload protection function (safety circuit breaker) will activate and cut off the AC input port.

Please follow the sequence below to restore the AC input function

1. Turn off the power button and unplug all ports.
2. After confirming that there is no abnormality in each part, turn on the power button.
3. Press the overload protection button, and connect the AC cable to restore the AC input.

Introduction of Display Interface



1. Remain Using/Recharging Time
2. Fan Status
3. High/Low-Temperature Protection
4. Battery Level Percentage
5. Input Power in Total
6. Output Power in Total

7. LED Light
8. AC Output
9. PD Output
10. USB Output
11. Connected to the AC Mains
12. Anderson Port
13. DC (12V) Output
14. Cigar Lighter (12V) Output
15. XT60 (12V) Output
16. Battery Progress Bar

The Screen Displays Precautions

-  When this icon lights up, please ensure that the vent is not blocked.
-  When this icon flashes, it means that the temperature is too high or too low, and the product may turn on the smart protection program and stop working. (Need to wait for the product to return to the normal temperature range to continue working)
-  If the icon blinks, it indicates that the AC mains connection is abnormal. Check the charging port.
- When this icon flashes, it means abnormal, please check the load.



UPS Mode


UPS Feature

This product has a bypass mode, which can output directly from AC mains without going through the battery. In the UPS state, when the AC input power of the commercial power is cut off due to a power failure, it can automatically switch to the product battery power supply within about 8 milliseconds to ensure the AC output.

UPS Connection Diagram

As shown in the figure below, connect the product between the socket and the electrical appliance, and the power of the product is in the ON state. When you turn on a powered device, the powered device uses the main AC power directly. In this state, when the main power supply is cut off, it will automatically switch to the product's internal battery power supply.

- In the UPS mode of U. S. and JPN standard, the maximum power of AC output is below 1100W, and the AC output exceeds 1100W, and the "  " AC output icon flashes to indicate overload.
- In the UPS mode of CN, UK, EU and KR standards the maximum power of AC output is below 2400W, and the AC output exceeds 2400W, and the "  " AC output icon flashes to indicate overload.




Connection of Solar Panels

- The company's products can be connected to solar panels and can be charged through the solar panels.
- The power of the solar panel is 500W, and can fully charge the product within 4 hours. (The input of the solar panel can be maximum 500W, maximum voltage 50V)
- The charging power of the solar panel is determined according to the weather and other conditions.
- The solar panel voltage exceeding 50V will damage the equipment and may be out of warranty.


By solar panels

Option one: Portable Power Station Charging Area




By solar panels

Option two: Portable Power Station Charging Area




Car Charging

- This product uses the ACC charging cable, which can be used for mobile charging by the cigarette lighter (Accessory: hereinafter referred to as ACC) in the car.
- Before using the product, whether it is charging or discharging, you must open the fan covers on both sides at the same time to prevent the product from being over heated and damaging the product.
- Connect the ACC charging cable to the cigarette lighter in the car and the Anderson interface on the side of the product, turn on the engine of the car, and the LED display of this product will display the input power.



Use of Fan Covers



Before operating the product, whether it is charging or discharging you must open the fan covers on both sides at the same time to prevent the product from over heating and causing the product to stop working or enter a protection state.

Product Specifications

Product Name	F2400 Portable Power Station
Dimension	L*W*H=386X284X321mm
Weight	22.0Kg
Capacity	2048Wh
AC Charging	AC Mains Input, 1100W max
MPPT Input	11.5-50V/20A/500W max
AC Output	50/60Hz (switchable), rated 2400W, pure sine wave with overload, short circuit protection
USB QC3.0	18W*2
Type-C	Type-C-A(PD 20W)*3
Type-C	Type-C-B(PD 100W)*1
DC 5521	12V/3A*2
XT-60 Output	12V/25A
Car Charging Output	12V/10A
Shutdown Current	< 500uA
Working Temperature	-10~40 °C
Environment Humidity	≤90%RH
Cycle Times	> 3500 Times

Battery Specifications

Cell type	40135 LiFePo4
Rated voltage of single battery	3.2V
Rated capacity of single battery	20Ah
Rated voltage of battery pack	51.2V
Output voltage range of the battery pack	43.2-57.6V
Rated capacity of battery pack	2048Wh

Troubleshooting

Status	Explanation	Recover method
 The above output icon flashes and beeps.	The output exceeds the standard and it's short-circuited.	<ol style="list-style-type: none">1. Remove the product.2. Check whether the overload protector pops up, if so, press the AC output button after pressing the overload protection button.3. If the overload protector does not pop up, press AC output directly to restore the output function.
 The temperature warning icon flashes and beeps.	The temperature of the product is too high or too low.	Remove the product, turn the power off, and wait for the product to reach a suitable temperature.
 The icon of connecting to the mains flashes and cannot be charged.	The charging cable is poorly connected.	Verify the connection status of the cable and the power supply.
	The overload protection function is enabled.	<ol style="list-style-type: none">1. Turn off the power button and unplug all ports.2. After confirming that there is no abnormality in each part, turn on the power button.3. Press the overload protection button, connect the AC line to restore the AC input.

Warranty

Product Model	
User Name	
Address	
Phone Number	
Email	
Sales Contact	
Purchasing Date	
Please fill in all of the above items.	

This product comes with a 24-month warranty from the date of purchase

- If there is a quality problem within the scope of normal use, we provide warranty.
- After purchasing our company's products, please keep this product together with invoices and other items, and please provide information according to our company's reliance request when maintenance services are required.
- Warranty service may not be provided if the warranty card is damaged, altered, etc., and it is considered to be incorrect, or if the warranty card is not stamped by the store where it was sold.
- Damage caused by use beyond the normal use range is not covered by the warranty service.
- The content of the warranty scope is subject to the content recognized by the company.
- Even within the scope of the warranty, there are times when an equivalent product can be exchanged. Shipping and maintenance costs for products not covered by the warranty shall be borne by the customer.
- Product specifications and features are sometimes changed without prior notice.
- Please refer to our updated guideline on our website below.

Manufacturer: Shenzhen Qichang Intelligent Technology Co., Ltd.

Address: China – Shenzhen

Documents / Resources

	<p>FOSSiBOT F2400 Portable Power Station [pdf] User Manual F2400 Portable Power Station, F2400, Portable Power Station, Power Station, Station</p>
---	--